



# THINKY



## APPLICATION

1 actuator for sectional doors and rolling doors, folding doors with more than two sections, unbalanced shutters and industrial sliding gates

## CONTROL UNIT POWER SUPPLY

230 Vac single-phase or 400 Vac three-phase

## MOTORS POWER SUPPLY

230 Vac / 800W or 400 Vac / 2200W


## MAIN FUNCTIONS

Integrated LCD display | Integrated 433.92 MHz 64-code radio receiver with ARC and predesigned for plug-in radio receiver | Autosetting of operating parameters with motors equipped with absolute encoder (VN "ESW" motors) | Removable terminal boards | Automatic, semi-automatic and deadman's logic | Motor limit switch inputs | Open, close, step by step, pedestrian and stop inputs | Inputs for 4 pairs of photocells (configurable as active in opening-closing or in closing phases) and equipped with PHOTO TEST logic | Input for N.C or 8K2 sensitive edge | Input for safety sensor | Output configurable as gate open indicator, second radio channel, service light and area light | Output configurable as gate open indicator or photocell testing output | Output for connecting flashing light | Protection against phase failure and exceeding motor current threshold | Advantouch system to configure parameters and manage radio transmitters | Number of maneuvers | Programming access password | Maintenance warning



### DA.2S

Electronic board that allows synchronised movement of 2 automation devices (opposed sliding gates).



### ONE.2WI

433.92 MHz receiver with triple coding: Advanced Rolling Code and Rolling Code, plug-in. 512 memorisable codes.



### THINKY.P

THINKY control units with open, close, stop buttons incorporated in the control unit.



### THINKY.I

THINKY control unit with self-holding open, close and stop buttons and tri-pole switch with door lock incorporated into the control unit.

**AUTOMATISMI BENINCA SpA** • Via del Capitello, 45 • 36066 Sandrigo (VI) ITALY • T +39 0444 751030 • sales@beninca.com

